

**DVR-1104ML**

**4 Channel Stand-Alone D V R system with LCD Display**

**Features:**

- 4 channels with BNC cameras inputs
- 2 channels with BNC Monitor / VCR outputs
- VGA output and 1 channel PCA audio input / out optional
- Removable HDD with ATA-100 interface, support over 200G byte
- PTZ control with RS-485 port
- USB2.0 port for PC backup
- 4 sets NO / NC sensor input
- Provides Time Schedule Record, Sensor Triggered Record and Motion Triggered Record
- Alarm output and video loss alarm function
- Motion detection with area setting function
- IR remote controller



**Specifications:**

Video Format	NTSC / PAL
Operation System	Stand-Alone
Camera Input	4 Channels (BNC)
Audio input / output	In 1CH / Out 1CH (Optional)
Video output	2 Channels (BNC / USB2.0 Port)
Hard Disk Support	Over 200G byte with ATA-100 interface
Recording Mode	Continuous, Schedule, Motion Triggered, Sensor Triggered
Video Compression	Modified Motion-JPEG
Display Resolution	NTSC: 720 x 480 Pixels
Recording Resolution	NTSC: 640 x 224 Pixels
Display Frame Rate	NTSC: 30 fps (Each),
Recording Frame Rate	NTSC: Max. 30 fps (Quad). Max. 30 frames / channel
Monitor Mode	10.4" color LCD with 800 x 600 pixels, 250:1
Display Mode	Full / Quad
Sensor / Alarm	4 Channels input / 1 Channel output
PTZ Control	Yes
USB Port	Yes
Audio	1 Channel output / 1 Channel output optional
VGA	Optional
Dimensions	
Picture-In-Picture	Yes, movable
Key Lock	Yes
Picture Zoom	2 x 2 (movable)
Camera Title	6 letters
Video Adjustment	Color / Contrast / Brightness
Alarm Input	TTL Input, Hi (5 V), Low (Gnd)
Alarm Output	COM / N. O.
Time Display Format	YY/MM/DD, DD/MM/YY, MM/DD/YY, OFF
Power Source	AC 100~240V +/- 10% switch adapter
Power Consumption	< 32W
Operation Temperature	50 ~ 104 °F (10 ~ 40 °C)
Dimension	13.5" W x 8.8" D x 2.4"H
Net Weight	4.5 Lb

**Matco, Inc.**

649 S. Vermont St.  
Palatine, IL 60067  
U.S.A.

Phone: (847) 202-0010  
Fax: (847) 202-0018  
Email: [EverSecure@matco.com](mailto:EverSecure@matco.com)  
[www.matco.com](http://www.matco.com)